

03/08/00

3-10-00

A

3780 U.S. P.O.

Please type a plus sign (+) inside this box → ☐Approved for use through 09/30/2000. OMB 0651-0032
Patent and Trademark Office: U.S. DEPARTMENT OF COMMERCE
Under the Paperwork Reduction Act of 1995, no persons are required to respond to a collection of information unless it displays a valid OMB control number.**UTILITY
PATENT APPLICATION
TRANSMITTAL**

(Only for new nonprovisional applications under 37 C.F.R. § 1.53(b))

Attorney Docket No. 6960 US

First Inventor or Application Identifier EDWARD J. CLEARY, JR.

Title SURROUND SOUND DISPLAY

Express Mail Label No. EL415463782US

APPLICATION ELEMENTS

See MPEP chapter 600 concerning utility patent application contents.

1. ☒ * Fee Transmittal Form (e.g., PTO/SB/17)
(Submit an original and a duplicate for fee processing)
2. ☒ Specification [Total Pages 13]
(preferred arrangement set forth below)
- Descriptive title of the invention
 - Cross References to Related Applications
 - Statement Regarding Fed sponsored R & D
 - Reference to Microfiche Appendix
 - Background of the invention
 - Brief Summary of the invention
 - Brief Description of the Drawings (if filed)
 - Detailed Description
 - Claim(s)
 - Abstract of the Disclosure
3. ☒ Drawing(s) (35 U.S.C. 113) [Total Sheets 4]
4. Oath or Declaration [Total Pages 2]
- a. ☒ Newly executed (original or copy)
- b. ☐ Copy from a prior application (37 C.F.R. § 1.63(d))
(for continuation/divisional with Box 16 completed)
- i. ☐ **DELETION OF INVENTOR(S)**
Signed statement attached deleting
inventor(s) named in the prior application,
see 37 C.F.R. §§ 1.63(d)(2) and 1.33(b).

*** NOTE FOR ITEMS 1 & 13: IN ORDER TO BE ENTITLED TO PAY SMALL ENTITY
FEES, A SMALL ENTITY STATEMENT IS REQUIRED (37 C.F.R. § 1.27), EXCEPT
IF ONE FILED IN A PRIOR APPLICATION IS RELIED UPON (37 C.F.R. § 1.28).****ADDRESS TO:**Assistant Commissioner for Patents
Box Patent Application
Washington, DC 20231

5. ☐ Microfiche Computer Program (Appendix)
6. Nucleotide and/or Amino Acid Sequence Submission
(if applicable, all necessary)
- a. ☐ Computer Readable Copy
- b. ☐ Paper Copy (identical to computer copy)
- c. ☐ Statement verifying identity of above copies

ACCOMPANYING APPLICATION PARTS

7. ☐ Assignment Papers (cover sheet & document(s))
8. ☐ 37 C.F.R. § 3.73(b) Statement ☐ Power of
(when there is an assignee) ☐ Attorney
9. ☐ English Translation Document (if applicable)
10. ☒ Information Disclosure ☐ 2 Copies of IDS
Statement (IDS)/PTO-1449 Citations
11. ☐ Preliminary Amendment
12. ☒ Return Receipt Postcard (MPEP 503)
(Should be specifically itemized)
13. ☐ * Small Entity ☐ Statement filed in prior application,
Statement(s) Status still proper and desired
(PTO/SB/09-12)
14. ☐ Certified Copy of Priority Document(s)
(if foreign priority is claimed)
15. ☐ Other: _____

16. If a CONTINUING APPLICATION, check appropriate box, and supply the requisite information below and in a preliminary amendment:

☐ Continuation ☐ Divisional ☐ Continuation-in-part (CIP) of prior application No. _____
Prior application information: Examiner _____ Group / Art Unit: _____

For CONTINUATION or DIVISIONAL APPS only: The entire disclosure of the prior application, from which an oath or declaration is supplied under Box 4b, is considered a part of the disclosure of the accompanying continuation or divisional application and is hereby incorporated by reference. The incorporation can only be relied upon when a portion has been inadvertently omitted from the submitted application parts.

17. CORRESPONDENCE ADDRESS☐ Customer Number or Bar Code Label

(Insert Customer No. or Attach bar code label here)

or ☒ Correspondence address below

| | | | | | |
|---------|-----------------|-----------|--------------|----------|--------------|
| Name | Francis I. Gray | | | | |
| | TEKTRONIX, INC. | | | | |
| Address | MS 50-LAW | | | | |
| | P.O. Box 500 | | | | |
| City | Beaverton | State | Oregon | Zip Code | 97077 |
| Country | U.S.A. | Telephone | 503 627-7261 | Fax | 503 627-7119 |

| | | | |
|-------------------|------------------------|-----------------------------------|---------------|
| Name (Print/Type) | Francis I. Gray | Registration No. (Attorney/Agent) | 27,788 |
| Signature | <i>Francis I. Gray</i> | Date | March 8, 2000 |

Burden Hour Statement: This form is estimated to take 0.2 hours to complete. Time will vary depending upon the needs of the individual case. Any comments on the amount of time you are required to complete this form should be sent to the Chief Information Officer, Patent and Trademark Office, Washington, DC 20231. DO NOT SEND FEES OR COMPLETED FORMS TO THIS ADDRESS. SEND TO: Assistant Commissioner for Patents, Box Patent Application, Washington, DC 20231.

TITLE OF THE INVENTION

SURROUND SOUND DISPLAY

BACKGROUND OF THE INVENTION

5 The current invention relates to displays of audio information, and more particularly to a surround sound display for displaying certain characteristics, such as amplitude and phase relationships, of multi-channel sound.

10 Correlation between two signals is a measure of how much alike the two signals are, expressed mathematically. If both signals are identical except for amplitude scaling, the correlation is positive and unity. If the signals are completely unrelated, the correlation is zero. A negative unity indicates that the signals are identical except for amplitude scaling, but of opposite polarity. Therefore the correlation between two signals may have
15 any value between +1 and -1.

20 There have been attempts to give a visual indication of multi-channel sound characteristics. The Master Stereo Display MSD-600 with a CDR-1616 Digital Audio Matrix provides separate graphic and bar graph displays of multi-channel sound. Also the Leader 5836A Surround Audio Monitor displays a sound image of multi-channel sound for 3-1/3-2 types of surround audio systems. The MSD multichannel "jellyfish" display has no phase information, just relative amplitude between channels. The Leader multi-channel Lissajous-like display is useful, but very difficult to interpret — it does not give an easy to understand representation of the sound field.

What is desired is a surround sound display that gives a user a quick visual representation of a surround sound audio program in a single display for both amplitude and phase elements.

5 BRIEF SUMMARY OF THE INVENTION

Accordingly the present invention provides a surround sound display that gives a user a quick simple display of the phase and amplitude characteristics of a surround sound system. The display includes a sound stage image, using speaker images or symbols at
10 appropriate locations on the display and a listener image in the center of the display. For each channel of a stereo pair a bent correlation meter scale, either visible or invisible, is used with a +1 correlation at one end of the scale situated at the center, a zero correlation in the middle of the scale at the corner, and a -1 correlation at the other end of the scale situated
15 around the corner at approximately ninety degrees with respect to the listener image. Corresponding markers for the bent correlation meter scales are used to represent the amount of correlation between the channels of the stereo pair, the distance or "width" between the markers representing the correlation between the stereo channels. Brightness or
20 color may be used as an indication of amplitude of each channel of the surround sound system, or wedges that extend toward the listener image may be used where the "height" of the wedges represents amplitude and the angular "width" represents phase.

003027 03000

The objects, advantages and other novel features of the present invention are apparent from the following detailed description when read in conjunction with the appended claims and attached drawing.

5 BRIEF DESCRIPTION OF THE SEVERAL VIEWS OF THE DRAWING

Fig. 1 is a graphic view display for a simple stereo system according to the present invention.

10 Figs. 2A, 2B and 2C represent an alternative graphic view display for different correlation values for the simple stereo system according to the present invention.

Fig. 3 is a graphic view display for the simple stereo system using an annular ring pattern according to the present invention.

Fig. 4 is a graphic view display for the simple stereo system using a ring angle pattern according to the present invention.

15 Fig. 5 is a graphic view display for the simple stereo system using a pie slice pattern according to the present invention.

Fig. 6 is a graphic view display for the simple stereo system using a rectangular pattern according to the present invention.

20 Fig. 7 is a graphic view display for a five channel surround sound system according to the present invention.

Fig. 8 is an alternative graphic view display for the five channel surround sound system according to the present invention.

Fig. 9 is a further alternative graphic view display for the five channel surround sound system according to the present invention.

DETAILED DESCRIPTION OF THE INVENTION

5 Referring now to Fig. 1 a two-channel stereo system display is shown with Left and Right channels only. A "bent" correlation meter scale **12L, 12R** is associated with each channel in front of a speaker image **10L, 10R** for each channel at the upper corners of the display. Image "width" as represented by the distance between a pair of pointers **14L,**
10 **14R**, one for each correlation meter scale, is related to phase correlation between the channels. Fully correlated L and R channels produce a point image in the center of the "sound stage" represented by the speaker images **10L, 10R**, sometimes called a phantom center. As L and R correlation decreases, the distance between the markers **14L, 14R** widens until at zero
15 correlation the pattern is as wide as the space between the speaker images. As correlation goes negative, the pattern or distance between the pointers **14L, 14R** extends outward around the "bend" beyond the speaker images **10L, 10R**.

20 Instead of the bent correlation meter scales **12L, 12R**, the space between the pointers **14L, 14R** may be filled in with bright or colored areas, as indicated in Figs. 2A, 2B and 2C for correlation values of 0.5, 0 and -1. Also the pattern may be filled or shaped differently as shown in Figs. 3-6 representing respectively (a) an annular ring pattern **18** for a

correlation value of -1, (b) a ring angle pattern **20** proportional to correlation for a correlation value of -0.5, (c) a pie slice pattern **22** for a correlation value of +0.3, and (d) a rectangular ring pattern **24** for a correlation value of -1.

5 In addition to phase correlation the pattern may indicate intensity or level as well either by means of brightness or color of “wedges” **26L**, **26R**, **26C**, **26LS**, **26RS** associated with each channel, or by turning the wedges into amplitude meters deflecting inward toward a “listener” **28** represented by a head image at the center of the display, as shown in Fig.
10 7 for a 5-channel system. The C (Center) channel wedge **26C** is fixed in location and width. Amplitude **A** is indicated by change in height toward the listener **28** in the center. The inner sides of the L and R wedges **26L**, **26R** are fixed, but the outer sides move along an invisible or visible phase correlation meter scale **12L**, **12R** to indicate correlation from +1 to -1 as
15 shown. The amplitudes of the L and R signals are indicated by the heights of the wedges moving towards the listener. The wedges are essentially level bars whose width depends on phase correlation between the signals and whose height depends on the amplitudes of the individual signals. The same scheme is used for the Left Surround and Right Surround
20 channels at the bottom of the display.

A variation of this scheme is shown in Fig. 8 where the zero correlation condition is indicated by wedges **26L**, **26R** centered on left and right 45° axes. When correlation is positive, the wedges widen along the

correlation meter scales **12L**, **12R** towards the center wedge **26C** while the opposite edge remains fixed. When correlation is negative, the edge away from the center wedge moves outward, widening the wedges toward the 90° axes while the edge toward the center remains fixed. In all cases the amplitude is indicated by the height of the wedge toward the listener. The same scheme is used for the Surround channels at the bottom of the display.

Another variation of this display, shown in Fig. 9, eliminates phase information altogether, showing only the amplitude relationships between channels. This pattern keeps the wedges at a fixed width, and the amplitude of each channel is shown by expanding the wedge height toward the listener at the center. This is essentially a circular bar graph. Optionally a wedge **26CS** for a "Low Frequency Enhancement" sixth channel, for 5.1 channel sound, may be added at the center rear between the Surround channel wedges **26LS**, **26RS**.

These displays shown in Figs. 1-9 give a user a quick visual representation of a surround sound audio program. The displays of Figs. 7 and 8 offer in a single display both amplitude and phase elements critical to proper system monitoring. Phase reversals, radical unbalance or missing channels are immediately evident. Properly interpreted these displays also provide a visual image of the sound field. Such displays supplement, but do not replace, conventional bar graphs and Lissajous patterns that are still needed for detailed analysis or accurate measurements.

The data for the display is obtained by digitizing the audio from each channel, performing a correlation function between the audio channels of a stereo pair to obtain a correlation value, converting the correlation values to a graphic display according to the desired display function from among Figs. 1-9, adding the graphic images to the graphic display, and periodically displaying the graphic display on a suitable display device. The graphic display may be updated sixty times a second to provide an instantaneous display of the surround sound audio program. Peak values may be displayed as well, such as by using an arc segment at the inner ends of the wedges. The display is created from the amplitude of each channel, which is straightforward, and the computed correlation between the L & R and LS & RS channels. One correlation computation that may be used is the same as that used in the 764 Digital Audio Monitor manufactured by Tektronix, Inc. of Beaverton, Oregon as described in the accompanying User Manual. The amplitude data is processed in the same way as for a level meter, i.e., metering ballistics are applied. The correlation data also may be smoothed.

The present invention may be extended to any number of systems having different channels, such as the common 3/1 system (three front channels L, C, R and one surround channel S) simply by fixing the width of the rear wedges and using them both to represent the S channel. They might even be joined to become one wide wedge. The extensions may be from simple stereo systems to 7.1 channel systems.

5

CLAIM OR CLAIMS

WHAT IS CLAIMED IS:

1. A surround sound display comprising:

5 a sound stage image;
 a correlation meter scale for each stereo channel of the sound stage
image; and
 markers related to the correlation meter scales that represent the
correlation between the stereo channels.

10

2. The display as recited in claim 1 wherein the sound stage image
comprises speaker images positioned at appropriate positions of the
display to represent sound sources.

15

3. The display as recited in claims 1 or 2 wherein the sound stage image
comprises a listener image positioned in the center of the display.

20

4. The display as recited in claim 1 wherein the correlation meter scale
comprises a bent scale for each stereo channel representing correlation
values between +1 and -1 at opposing ends of the bent scale.

5. The display as recited in claim 4 wherein the bent scale has the +1 end
centrally located along a first side of the display, the -1 end

centrally located along a second side of the display, the second side being orthogonal to the first side, and a central portion representing a correlation value of 0 adjacent a corner between the first and second sides.

5 6. The display as recited in claim 4 wherein a second bent scale
representing a related stereo channel has the +1 end centrally located
along the first side of the display adjacent the first bent scale, the -1 end
centrally located along a third side of the display opposite the second
side, and a central portion representing a correlation value of 0 adjacent a
10 corner between the first and third sides.

15 7. The display as recited in claim 1 wherein the markers comprise a
pointer for each stereo channel, the location of the pointer along the
correlation meter scale indicating the correlation between the stereo
channels.

20 8. The display as recited in claim 7 wherein the markers comprise a fill
area spanning the correlation meter scales for the stereo channels, the
width of the fill area indicating the correlation between the stereo
channels.

9. The display as recited in claim 8 wherein the thickness of the fill area
indicates the amplitude of the stereo channels.

10. The display as recited in claim 1 wherein the correlation meter scales for the stereo channels comprise bent scales each having a +1 value adjacent the other centrally along a first side of the display, respective -1 values centrally along opposing adjacent sides orthogonal to the first side, and 0 values adjacent respective corners between the first and each adjacent side.

11. The display as recited in claim 10 wherein the markers comprise a fill area that spans the correlation meter scales and has a width and a thickness, the width indicating the correlation between the stereo channels.

12. The display as recited in claim 11 wherein the fill area has two contiguous portions, a first portion overlaying one of the correlation meter scales and a second portion overlaying the other one of the correlation meter scales, the thickness of the portions indicating the amplitude of the related stereo channels.

13. The display as recited in claim 1 wherein the markers comprise a plurality of truncated wedges, at least one of the truncated wedges having a fixed width representing a central audio source and the other truncated wedges representing the stereo channels with a variable width, the variable width indicating the correlation between the stereo channels.

14. The display as recited in claim 13 wherein the truncated wedges representing the stereo channels have a first radial edge fixed at a +1 value for the stereo channels and a second radial edge variable between the +1 value and a -1 value to alter the variable width of the truncated wedges to indicate the correlation between the stereo channels.

15. The display as recited in claim 13 wherein the truncated wedges for the stereo channels have a minimum width centered at a specified angle representing a 0 value of the correlation meter scales, and a first radial edge is fixed when the correlation is negative while a second radial edge varies to change the variable width of the truncated wedge and the second radial edge is fixed when the correlation is positive while the first radial edge varies to change the variable width of the truncated wedge.

ABSTRACT OF THE DISCLOSURE

A surround sound display has a graphic sound stage image, including speakers representing sources and a central listener, and bent correlation meter scales for each stereo channel. The correlation meter scales have values from +1 at one end to -1 at the other end and are bent to start from a central point along one side of the display between the speakers representing the stereo channels to a point along the opposing adjacent sides of the display outside the respective speakers. A marker, either in the form of individual pointers for each scale or as a fill area that spans the scales, indicates the correlation between the stereo channels. The thickness of the fill area indicates the amplitudes of the stereo channels. Where a central sound source is part of the surround sound system, the marker may be in the form of truncated wedges, the wedge for the central sound source having a fixed width and the widths of the wedges for the stereo channels being variable so that the widths indicate the correlation between the stereo channels. The heights of the wedges toward a central listener in the display indicate the amplitudes for each of the sound channels of the surround sound system.




FIG. 1




FIG. 2A

FIG. 2B

FIG. 2C




FIG. 3




FIG. 4




FIG. 5






FIG. 6



[illegible]

DECLARATION FOR PATENT APPLICATION

As a below named inventor, I hereby declare that:

My residence, post office address and citizenship are as stated below next to my name.

I believe I am the original, first and sole inventor (if only one name is listed below) or an original, first and joint inventor (if plural names are listed below) of the subject matter which is claimed and for which a patent is sought on the invention entitled: _____

SURROUND SOUND DISPLAY

the specification of which:

(check one)

X is attached hereto.

_____ was filed on _____ as Application Serial No. _____ and was amended on _____ (if applicable).

I hereby state that I have reviewed and understand the contents of the above-identified specification, including the claims, as amended by any amendment referred to above.

I acknowledge the duty to disclose information which is material to the examination of this application in accordance with Title 37, Code of Federal Regulations, Section 1.56(a).

I have identified below any foreign application(s) for patent or inventor's certificate from which I claim foreign priority benefits under Title 35, United States Code, Section 119 and have also identified below any foreign application for patent or inventor's certificate having a filing date before that of the application on which priority is claimed:

Prior Foreign Application(s)

Priority Claimed

| | | | | |
|-------------------|--------------------|---------------------------------|--------------|-------------|
| _____ (Number) | _____ (Country) | _____ (Day/Month/Year Filed) | _____ Yes | _____ No |
| _____ (Number) | _____ (Country) | _____ (Day/Month/Year Filed) | _____ Yes | _____ No |

I hereby claim the benefit under Title 35, United States Code, Section 120 of any United States application(s) listed below and, insofar as the subject matter of each of the claims of the above-identified specification is not disclosed in the prior United States application(s) in the matter required by the first paragraph of Title 35, United States Code, Section 112, I acknowledge the duty to disclose material information as defined in Title 37, Code of Federal Regulations, Section 1.56(a) which occurred between the filing date of the prior application(s) and the national or PCT international filing date of this application:

| | | |
|-----------------------------------|------------------------|--|
| _____ (Application Serial No.) | _____ (Filing Date) | _____ (Status-patented, pending, abandoned) |
| _____ (Application Serial No.) | _____ (Filing Date) | _____ (Status-patented, pending, abandoned) |

I hereby appoint the following attorney(s) and/or agent(s) to prosecute this application and to transact all business in the Patent and Trademark Office connected therewith:

William K. Bucher, Reg. No. 32,686; Francis I. Gray, Reg. No. 27,788; Thomas F. Lenihan, Reg. No. 32,152; John D. Winkelman, Reg. No. 26,523; John Smith-Hill, Reg. No. 27,730. at telephone no. (503) 627-7262, P.O. Box 500, Delivery Station 50-LAW, Beaverton, Oregon 97077.

Address all telephone calls to Francis I. Gray at Telephone no. (503) 627-7261.

Address all correspondence to Francis I. Gray, Tektronix, Inc., P.O. Box 500, Delivery Station 50-LAW, Beaverton, Oregon 97077.

I hereby declare that all statements made herein of my own knowledge are true and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under Section 1001 of Title 18 of the United States Code and that such willful false statements may jeopardize the validity of the application or any patent issued thereon.

Full name of sole or first inventor EDWARD J. CLEARY, JR.

Inventor's signature Edward J. Cleary, Jr. Date 2/26/00

Residence Beaverton, Oregon Citizenship U.S.A.

Address P.O. Box 262
Beaverton, Oregon 97075

Full name of second inventor STEVEN A. KRONSCHNABEL

Inventor's signature Steven A. Kronschnabel Date 3-6-2000

Residence Beaverton, Oregon Citizenship U.S.A.

Address 17915 N.W. Sue Court
Beaverton, Oregon 97006